

CLAIMS AS CURRENTLY AMENDED

1. (canceled)
2. (canceled)
3. (currently amended) ~~The method of claim 2, further comprising:~~ A method for automatic I/Q balancing for packets of an incoming signal, comprising:
 - resolving an on-line incoming signal into I and Q signals;
 - computing packet-fixed correction coefficients from said I and Q signals during a measurement section for a packet;
 - correcting at least one of I/Q gain and I/Q phase of said I and Q signals with said packet-fixed correction coefficients for providing corrected said I and Q signals for said packet;
 - delaying said I and Q signals by at least said measurement section;and wherein the step of correcting includes correcting said at least one of said I/Q gain and said I/Q phase of said delayed I and Q signals with said packet-fixed correction coefficients for providing said corrected I and Q signals;
 - detecting pre-delay averages for said I and Q signals for a time period not greater than said measurement section before the step of delaying said I and Q signals; and
 - using said pre-delay averages for reducing DC offset from said delayed I and Q signals before the step of correcting said I and Q signals.
4. (canceled)
5. (currently amended) ~~The method of claim 4, further comprising:~~ A method for automatic I/Q balancing for packets of an incoming signal, comprising:

resolving an on-line incoming signal into I and Q signals;
computing packet-fixed correction coefficients from said I and Q
signals during a measurement section for a packet;
correcting at least one of I/Q gain and I/Q phase of said I and Q
signals with said packet-fixed correction coefficients for providing corrected said I
and Q signals for said packet, wherein the step of correcting includes using said
packet-fixed correction coefficients for correcting said at least one of said I/Q gain
and said I/Q phase for a portion of said packet only after said measurement
section of said packet for providing said corrected I and Q signals;
detecting averages for said I and Q signals for a time period not
greater than said measurement section; and
using said averages for reducing DC offset of said I and Q signals
for a time period of said packet after said measurement section before the step of
correcting said I and Q signals.

6. (canceled)

7. (previously presented) A method for automatic I/Q balancing for packets of an
incoming signal, comprising:

resolving said incoming signal into I and Q signals;
computing packet-fixed correction coefficients from said I and Q
signals during a measurement section for a packet;
correcting at least one of I/Q gain and I/Q phase of said I and Q
signals with said packet-fixed correction coefficients for providing corrected said I
and Q signals for said packet; and wherein:
the step of computing packet-fixed correction coefficients includes
computing first and second correction coefficients using a finite number of
indexed I values for said I signal and said finite number of indexed Q values for
said Q signal; where

a first term includes a cross correlation of said I values and said Q values;

a second term includes an autocorrelation of said Q values;

a third term includes said first term divided by said second term;

a fourth term includes a sum of absolute values of said Q values;

a fifth term includes a sum of absolute values of difference values, said difference values including said I values minus product values, said product values including said Q values times said third term; and

said first correction coefficient includes said fourth term divided by said fifth term.

8. (original) The method of claim 7, wherein:

said second correction coefficient includes the negative of said third term.

9. (original) The method of claim 7, wherein:

said second correction coefficient includes a negative of a product of said first correction coefficient and said third term.

10. (canceled)

11. (canceled)

12. (canceled)

13. (currently amended) ~~The receiver of claim 12, further comprising:~~ A signal receiver having automatic I/Q balancing for packets of an incoming signal, comprising:

a quadrature converter for resolving an on-line incoming signal into I and Q signals;

an IQ coefficient calculator for computing packet-fixed correction coefficients from said I and Q signals during a measurement section of a packet;

an IQ balancer for using said packet-fixed correction coefficients for correcting at least one of I/Q gain and I/Q phase of said I and Q signals for providing corrected said I and Q signals for said packet;

I and Q delay devices for delaying said I and Q signals by at least said measurement section; wherein the IQ balancer corrects said at least one of said I/Q gain and said I/Q phase of said delayed I and Q signals with said packet-fixed correction coefficients for providing said corrected I and Q signals;

an average detector for detecting pre-delay averages for said I and Q signals for a time period not greater than said measurement section before the step of delaying said I and Q signals; and

an average corrector for using said pre-delay averages for reducing DC offset from said delayed I and Q signals before the step of correcting said I and Q signals.

14. (canceled)

15. (currently amended) ~~The receiver of claim 14, further comprising:~~ A signal receiver having automatic I/Q balancing for packets of an incoming signal, comprising:

a quadrature converter for resolving an on-line incoming signal into I and Q signals;

an IQ coefficient calculator for computing packet-fixed correction coefficients from said I and Q signals during a measurement section of a packet;

an IQ balancer for using said packet-fixed correction coefficients for correcting at least one of I/Q gain and I/Q phase of said I and Q signals for

providing corrected said I and Q signals for said packet, wherein the IQ balancer uses said packet-fixed correction coefficients for correcting said at least one of said I/Q gain and said I/Q phase of said I and Q signals for a time period of said packet only after said measurement section for providing said corrected I and Q signals;

an average detector for detecting averages for said I and Q signals for a time period not greater than said measurement section; and

an average corrector for using said averages for reducing DC offset of said I and Q signals for a time period of said packet after said measurement section before the step of correcting said I and Q signals.

16. (canceled)

17. (previously presented) A signal receiver having automatic I/Q balancing for packets of an incoming signal, comprising:

a quadrature converter for resolving said incoming signal into I and Q signals;

an IQ coefficient calculator for computing packet-fixed correction coefficients from said I and Q signals during a measurement section of a packet;

an IQ balancer for using said packet-fixed correction coefficients for correcting at least one of I/Q gain and I/Q phase of said I and Q signals for providing corrected said I and Q signals for said packet; and wherein:

the IQ coefficient calculator computes first and second said correction coefficients using a finite number of indexed I values for said I signal and said finite number of indexed Q values for said Q signal; where

a first term includes a cross correlation of said I values and said Q values;

a second term includes an autocorrelation of said Q values;

a third term includes said first term divided by said second term;

a fourth term includes a sum of absolute values of said Q values;
a fifth term includes a sum of absolute values of difference values,
said difference values including said I values minus product values, said product
values including said Q values times said third term; and
said first correction coefficient includes said fourth term divided by
said fifth term.

18. (original) The receiver of claim 17, wherein:

said second correction coefficient includes the negative of said third
term.

19. (original) The receiver of claim 17, wherein:

said second correction coefficient includes a negative of a product
of said first correction coefficient and said third term.

20. (canceled)